

Door Open Too Long Alarm DorWatcher

Overview

The DorWatcher is an alarm unit used to prevent doors being left open for an extended period of time.

DorWatcher can be used in any situation where it is undesirable for a door to be open for more than a short period. The time that the door can be left open for without generating an alarm can be adjusted at installation time.

Normal Operation

When the protected door is opened the units LED will flash every few seconds and time TD1 will be allowed to elapse before a short warning chime is made by the unit. An additional time TD2 is then allowed to elapse. If the door hasn't been closed after times TD1 and TD2 have elapsed, the unit will start sounding its main alarm tone. If the door is closed before the main alarm tone is heard, the unit will reset and the next time the door is opened the timers will start again. Once in full alarm, the tone will continue for 2 minutes after which time the alarm tone will cease and a chime will be heard every 30 seconds to alert people in the vicinity that the door is still open. To clear the alarm, close the door.

Simple Inspection

We recommend that DorWatcher's installed in locations prone to tampering/vandalism are both fitted with an anti - tamper screws and cages (available separately) and inspected for signs of tampering on a regular basis.

A simple visual check of the DorWatcher can be made:

Open the protected door, if the LED on the front panel flashes within 10 seconds then the system is working correctly, if the LED does not flash and the alarm does not activate after the preset time, contact your installation company for advice.

Battery fault indication

The battery powered DorWatcher model DW304 has a built in Battery fault monitor. If the unit beeps as soon as the door is opened, this indicates that the batteries are running low and should be changed for new batteries (6 x AA).

Time Delays

TD1 and TD2 times are adjustable as follows:

TD1 (Secs)	TD2 (Secs)	Total time to alarm
20	10	30 seconds
40	20	1 minute - Factory default
160	20	3 minutes
400	20	7 minutes

Features

- Robust ABS plastic enclosure.
- A box tamper switch activates the tamper tone if the front cover is removed.
- Clear instructions displayed on the unit.
- Models available - battery, 12vdc or 240vac mains.
- Surface mounting door contact provided with 1m of cable pre connected.
- Cable clips and fixing screws provided
- Audible battery fault monitor
- Quick and easy to install.
- Dimensions:
175 (w) x 125 (h) x 60mm (max) (d)



The Emergency Bolt Company Ltd

Unit 6 Vennland Business Park, Mart Road, Minehead, TA24 5DX

Tel: 01643 709591 Fax: 01643 708504 Email: Sales@theemergencyboltcompany.com

Web: www.theemergencyboltcompany.com